

# UROVO

## Wearable 2D Scanning Ring

# SR5600

- Megapixel laser sight scanning engine can decode 1D or 2D barcodes quickly with the performance the same as professional PDA device
- It supports finger wearing and glove wearing and provides the whole set of industrial wearable solution
- Dual-mode Bluetooth supports BLE low-consumption Bluetooth and classic Bluetooth
- 800 mAh large-capacity removable battery is built in to ensure endurance
- It supports diverse kinds of quick pairing modes (Bluetooth listing mode by default), including pairing by code scanning and NFC touch connection mode
- Several kinds of accessories are available. It supports four-slot charging cradle, six-slot battery charging cradle and multi-slot battery charging cradle



High-performance scanning



Dual-mode Bluetooth



800 mAh Large battery



Quick pairing mode



Several kinds of accessories available




# SR5600 Wearable 2D Scanning Ring

## Parameters


UROVO


 **Processor**  
High performance  
1.2 GHz processor

 **Overall dimensions**  
62.9 x 31 x 18.2mm


 **Material**  
Alloy and PC


 **Waterproof grade**  
IP65


 **Battery**  
polymer lithium battery  
3.8V/800mAh/Dismountable  
Continuous working duration: 4 h  
Standby time: More than 24 h  
Charging time: Less than 3 h

 **Communication mode**  
Dual-mode bluetooth  
NFC quick pairing (ISO15693)


 **Interface**  
pogo pin (4pin)

 **Prompt**  
Vibration  
Buzzer  
3-color indicator LED


 **Buttons**  
Scanning key x 1  
Power key (reset key) x 1


 **Scanning**  
SE2030/2D/White fill-in light/  
Aiming by cross laser  
Decoding range: 5~40 cm  
(subject to actual scenario)  
Decoding speed: Within 100 ms

 **Storage**  
Nor Flash 8MB

 **Environmental illumination**  
0-100000 LUX

 **ESD**  
Air  $\pm 15K$   
Contact  $\pm 8K$

 **Environment**  
Working temperature: -20°C~50°C  
5%-95%RH (non-condensation status)  
Storage temperature: -30°C~70°C  
5%-95%RH (non-condensation status)

 **Setting tools**  
Applet  
Local webpage  
Android APK  
The contents are the same as  
PDA scanning setting



Hand rope



Finger bracket



Glove



Ring charger



Four-slot charger